General purpose (dual digital transistors)

EMD6 / UMD6N / IMD6A

●Features


1) Both the DTA143T chip and DTC143T chip in an EMT or UMT or SMT package.
2) Mounting possible with EMT3 or UMT3 or SMT3 automatic mounting machines.
3) Transistor elements are independent, eliminating interference.
4) Mounting cost and area can be cut in half.

●Structure

A PNP and NPN digital transistor
(each with a single built in resistor)

The following characteristics apply to both the DTr_1 and DTr_2, however, the " –" sign on DTr_2 values for the PNP type have been omitted.

●Equivalent circuit




●Absolute maximum ratings (Ta = 25°C)

Parameter		Symbol	Limits	Unit
Collector-base voltage		V_{CBO}	50	V
Collector-emitter voltage		V_{CEO}	50	V
Emitter-base voltage		V_{EBO}	5	V
Collector current		I_C	100	mA
Collector power dissipation	EMD6, UMD6N	P_C	150 (TOTAL)	mW ＊1
	IMD6A		300 (TOTAL)	＊2
Junction temperature		Tj	150	˚C
Storage temperature		Tstg	−55~+150	˚C

＊1 120mW per element must not be exceeded.
＊2 200mW per element must not be exceeded.

●External dimensions (Units : mm)


EMD6



ROHM : EMT6

Abbreviated symbol : D6


UMD6N



ROHM : UMT6
EIAJ : SC-88

Abbreviated symbol : D6

IMD6A



ROHM : SMT6
EIAJ : SC-74

Abbreviated symbol : D6

●Electrical characteristics (Ta = 25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	50	–	–	V	I_C=50μA
Collector-emitter breakdown voltage	BV_{CEO}	50	–	–	V	I_C=1mA
Emitter-base breakdown voltage	BV_{EBO}	5	–	–	V	I_E=50μA
Collector cutoff current	I_{CBO}	–	–	0.5	μA	V_{CB}=50V
Emitter cutoff current	I_{EBO}	–	–	0.5	μA	V_{EB}=4V
Collector-emitter saturation voltage	$V_{CE\ (sat)}$	–	–	0.3	V	I_C/I_B=5mA/0.25mA
DC current transfer ratio	h_{FE}	100	250	600	–	V_{CE}=5V, I_C=1mA
Transition frequency	f_T	–	250	–	MHz	V_{CE}=10V, I_E=–5mA, f=100MHz ✻
Input resistance	R_1	3.29	4.7	6.11	kΩ	–

✻ Transition frequency of the transistor

●Packaging specifications

Type	Package	Taping		
	Code	T2R	TR	T108
	Basic ordering unit (pieces)	8000	3000	3000
EMD6		○	—	—
UMD6N		—	○	—
IMD6A		—	—	○

●Electrical characteristic curves

DTr1 (NPN)




Fig.1 DC current gain vs. collector current




Fig.2 Collector-emitter saturation voltage vs. collector current

DTr2 (PNP)




Fig.3 DC current gain vs. collector current




Fig.4 Collector-emitter saturation voltage vs. collector current

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).
Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.
In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.