

Silicon Schottky Diode


- General-purpose diode for high-speed switching
- Circuit protection
- Voltage clamping
- High-level detecting and mixing
- Pb-free (RoHS compliant) package
- Qualified according AEC Q101[1)]




BAS140W
BAS40-02L




BAS40




BAS40-04




BAS40-05
BAS40-05W



BAS40-06
BAS40-06W



BAS40-07
BAS40-07W



ESD (**E**lectro**s**tatic **d**ischarge) sensitive device, observe handling precaution!

Type	Package	Configuration	Marking
BAS140W	SOD323	single	white 4
BAS40	SOT23	single	43s
BAS40-02L*	TSLP-2-1	single, leadless	FF
BAS40-04	SOT23	series	44s
BAS40-05	SOT23	common cathode	45s
BAS40-05W	SOT323	common cathode	45s
BAS40-06	SOT23	common anode	46s
BAS40-06W	SOT323	common anode	46s
BAS40-07	SOT143	parallel pair	47s
BAS40-07W	SOT343	parallel pair	47s

[1]* BAS40-02L is not qualified according AEC Q101

Maximum Ratings at T_A = 25 °C, unless otherwise specified

Parameter	Symbol	Value	Unit
Diode reverse voltage	V_R	40	V
Forward current	I_F	120	mA
Non-repetitive peak surge forward current $t \leq$ 10ms	I_{FSM}	200	
Total power dissipation	P_{tot}		mW
BAS140W, T_S ≤ 113°C		250	
BAS40, BAS40-07, T_S ≤ 81°C		250	
BAS40-02L, T_S ≤ 127°C		250	
BAS40-04, BAS40-06, T_S ≤ 56°C		250	
BAS40-06W, T_S ≤ 106°C		250	
BAS40-05, T_S ≤ 31°C		250	
BAS40-05W, T_S ≤ 98°C		250	
BAS40-07W, T_S ≤ 118°C		250	
Junction temperature	T_j	150	°C
Operating temperature range	T_{op}	-55 ...150	
Storage temperature	T_{stg}	-55 ...150	

Thermal Resistance

Parameter	Symbol	Value	Unit
Junction - soldering point[1)]	R_{thJS}		K/W
BAS140W		≤ 150	
BAS40, BAS40-07		≤ 275	
BAS40-02L		≤ 90	
BAS40-04, BAS40-06		≤ 375	
BAS40-06W		≤ 175	
BAS40-05		≤ 475	
BAS40-05W		≤ 205	
BAS40-07W		≤ 125	

[1]For calculation of R_{thJA} please refer to Application Note AN077 (Thermal Resistance Calculation)


Electrical Characteristics at T_A = 25°C, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC Characteristics					
Breakdown voltage $I_{(BR)}$ = 10 µA	$V_{(BR)}$	40	-	-	V
Reverse current V_R = 30 V	I_R	-	-	1	µA
Forward voltage	V_F				mV
I_F = 1 mA		250	310	380	
I_F = 10 mA		350	450	500	
I_F = 40 mA		600	720	1000	
Forward voltage matching[1)] I_F = 10 mA	ΔV_F	-	-	20	
AC Characteristics					
Diode capacitance V_R = 0 , f = 1 MHz	C_T	-	3	5	pF
Differential forward resistance I_F = 10 mA, f = 10 kHz	R_F	-	10	-	Ω
Charge carrier life time I_F = 25 mA	τ_{rr}	-	-	100	ps

[1] ΔV_F is the difference between lowest and highest V_F in a multiple diode component.


Diode capacitance $C_T = f(V_R)$

f = 1MHz




Forward resistance $r_f = f(I_F)$

f = 10 kHz




Reverse current $I_R = f(T_A)$

V_R = Parameter




Reverse current $I_R = f(V_R)$

T_A = Parameter




Forward Voltage $V_F = f(T_A)$

I_F = Parameter




Forward current $I_F = f(V_F)$

T_A = Parameter




Forward current $I_F = f(T_S)$

BAS140W




Forward current $I_F = f(T_S)$


BAS40, BAS40-07




Forward current $I_F = f(T_S)$
BAS40-02L




Forward current $I_F = f(T_S)$
BAS40-04, BAS40-06



Forward current $I_F = f(T_S)$
BAS40-06W




Forward current $I_F = f(T_S)$
BAS40-05




Forward current $I_F = f(T_S)$

BAS40-05W




Forward current $I_F = f(T_S)$

BAS40-07W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS140W



Permissible Pulse Load


$I_{Fmax}/ I_{FDC} = f(t_p)$

BAS140W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS40-02L



Permissible Pulse Load


$I_{Fmax}/ I_{FDC} = f(t_p)$

BAS40-02L



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS40-06W



Permissible Pulse Load


$I_{Fmax}/ I_{FDC} = f(t_p)$

BAS40-06W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS40-05W




Permissible Pulse Load

$I_{Fmax}/ I_{FDC} = f(t_p)$


BAS40-05W




Package Outline



Foot Print




Marking Layout (Example)




Standard Packing


Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel




Package Outline



Foot Print




Marking Layout (Example)




Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel




Package Outline






1) Lead width can be 0.6 max. in dambar area

Foot Print




Marking Layout (Example)




Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel




Package Outline






Foot Print




Marking Layout (Example)




Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel
Reel ø330 mm = 10.000 Pieces/Reel




Package Outline




1) Dimension applies to plated terminal

Foot Print

For board assembly information please refer to Infineon website "Packages"




Marking Layout (Example)



Standard Packing

Reel ø180 mm = 15.000 Pieces/Reel
Reel ø330 mm = 50.000 Pieces/Reel (optional)



Edition 2009-11-16

Published by
Infineon Technologies AG
81726 Munich, Germany

© 2009 Infineon Technologies AG
All Rights Reserved.

Legal Disclaimer

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics. With respect to any examples or hints given herein, any typical values stated herein and/or any information regarding the application of the device, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation, warranties of non-infringement of intellectual property rights of any third party.

Information

For further information on technology, delivery terms and conditions and prices, please contact the nearest Infineon Technologies Office (<www.infineon.com>).

Warnings

Due to technical requirements, components may contain dangerous substances. For information on the types in question, please contact the nearest Infineon Technologies Office.
Infineon Technologies components may be used in life-support devices or systems only with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.