Micro-Power Voltage Detectors

General Description

The RT9819 is a micro-power voltage detector supervising the power supply voltage level for microprocessors (µP) or digital systems. It provides internally fixed threshold levels with 0.1V per step ranging from 1.2V to 5V, which covers most digital applications. It features low supply current of 3µA. The RT9819 performs supervisory function by sending out a reset signal whenever the V_{DD} voltage falls below a preset threshold level. This reset signal will last the whole period before V_{DD} recovering. Once V_{DD} recovered upcrossing the threshold level, the reset signal will be released after a certain delay time. RT9819 is provided in SC-70-3, SC-82 and SOT-23-3 packages.

Ordering Information

RT9819□-□□□□

- Package Type
  - U3 : SC-70-3
  - V : SOT-23-3
  - VL : SOT-23-3 (L-Type)
  - Y : SC-82
  - YR : SC-82 (R-Type)
- Lead Plating System
  - P : Pb Free
  - G : Green (Halogen Free and Pb Free)
- Threshold Voltage
  - 12 : 1.2V
  - 13 : 1.3V
  - :
  - 49 : 4.9V
  - 50 : 5.0V
- Reset Active Timeout Period
  - A = 0ms ($\overline{\text{RESET}}$)
  - B = 55ms ($\overline{\text{RESET}}$)
  - C = 220ms ($\overline{\text{RESET}}$)
  - D = 450ms ($\overline{\text{RESET}}$)
  - E = 0ms (RESET)
  - F = 55ms (RESET)
  - G = 220ms (RESET)
  - H = 450ms (RESET)

Note :

Richtek products are :

- RoHS compliant and compatible with the current requirements of IPC/JEDEC J-STD-020.
- Suitable for use in SnPb or Pb-free soldering processes.


Features

- **Internally Fixed Threshold 1.2V to 5V in 0.1V Step**
- **High Accuracy ±1.5%**
- **Low Supply Current 3µA**
- **No External Components Required**
- **Quick Reset within 20µs**
- **Built-in Recovery Delay Include 0ms, 55ms, 220ms, 450ms Options**
- **Low Functional Supply Voltage 0.9V**
- **CMOS Push-Pull Output**
- **Small SC-70-3, SC-82 and SOT-23-3 Packages**
- **RoHS Compliant and 100% Lead (Pb)-Free**

Applications

- Computers
- Controllers
- Intelligent Instruments
- Critical µP and µC Power Monitoring
- Portable/Battery-Powered Equipment

Typical Application Circuit




Marking Information

For marking information, contact our sales representative directly or through a Richtek distributor located in your area.

Pin Configurations

(TOP VIEW)




SC-70-3 SC-82 SC-82 (R-Type) SOT-23-3 SOT-23-3 (L-Type)

Functional Pin Description

Pin Name	Pin Function
GND	Ground
$\overline{\text{RESET}}$	Active Low Push-Pull Reset Output
RESET	Active High Push-Pull Reset Output
VDD	Power Pin

Function Block Diagram



Absolute Maximum Ratings (Note 1)

- Terminal Voltage (with Respect to GND)
  V_{DD} ---------- –0.3V to 6.0V
- All Other Inputs ---------- –0.3V to V_{DD}+0.3V
- Input Current, I_{VDD} ---------- 20mA
- Power Dissipation, PD @ T_A = 25°C
  SC-70-3/SC-82 ---------- 0.25W
  SOT-23-3 ---------- 0.4W
- Package Thermal Resistance (Note 2)
  SC-70-3/SC-82, θ_{JA} ---------- 400°C /W
  SOT-23-3, θ_{JA} ---------- 250°C /W
- Lead Temperature (Soldering, 10sec.) ---------- 260°C
- Storage Temperature Range ---------- –65°C to 125°C
- ESD Susceptibility (Note 3)
  HBM (Human Body Mode) ---------- 2kV
  MM (Machine Mode) ---------- 200V

Recommended Operating Conditions (Note 4)

- Junction Temperature Range ---------- –40°C to 125°C
- Ambient Temperature Range ---------- –40°C to 85°C

Electrical Characteristics

(V_{DD} = 3V, T_A = 25°C, unless otherwise specified)

Parameter		Symbol	Test Conditions	Min	Typ	Max	Units
Operating V_{DD} (V_{OUT}) Range		V_{DD}	RT9819A/B/C/D	0.9	--	6	V
			RT9819E/F/G/H	1.1	--	6	
Supply Current		I_{DD}	V_{TH} = 3V , V_{DD} = 4.5V	--	3	8	μA
Reset Threshold		V_{TH}		--	1.2 to 5.0	--	V
Threshold Voltage Accuracy		ΔV_{TH}		–1.5	--	+1.5	%
Threshold Voltage Hysteresis		V_{HYS}		--	0.01 V_{TH}	--	V
V_{DD} Drop to Reset Delay		t_{RD}	Drop = V_{TH} –125mV	--	20	--	μs
Reset Active Time Out Period	RT9819A/E	t_{RP}	$V_{DD} \geq 1.02 \times V_{TH}$	--	0	--	ms
	RT9819B/F			35	55	75	ms
	RT9819C/G			143	220	297	ms
	RT9819D/H			292	450	608	ms
$\overline{RESET}$ Output Voltage Low		V_{OL}	V_{DD} < $V_{TH(MIN)}$,I_{SINK} = 3.5mA, $V_{TH} \geq$ 3V	--	--	0.4	V
			V_{DD} < $V_{TH(MIN)}$,I_{SINK} = 1.2mA, $V_{TH} \geq$ 1.8V	--	--	0.3	
			$V_{TH(MIN)}$ > V_{DD} > 1V, I_{SINK} = 0.5mA	--	--	0.3	

To be continued

Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
$\overline{\text{RESET}}$ Output Voltage High	V_{OH}	$V_{DD} > V_{TH(MAX)}$, I_{SOURCE} = 800μA, $V_{TH} \geq 3V$	V_{DD} –1.5	--	--	V
		$V_{DD} > V_{TH(MAX)}$, I_{SOURCE} = 500μA, $V_{TH} \geq 1.8V$	0.8 V_{DD}	--	--	
		$V_{DD} > V_{TH(MAX)}$, I_{SOURCE} = 200μA, $V_{TH} \geq 1.1V$	0.8 V_{DD}	--	--	
RESET Output Voltage Low	V_{OL}	$V_{DD} > V_{TH(MAX)}$, I_{SINK} = 3.5mA, $V_{TH} \geq 3V$	--	--	0.4	V
		$V_{DD} > V_{TH(MAX)}$, I_{SINK} = 1.2mA, $V_{TH} \geq 1.8V$	--	--	0.3	
		$V_{DD} > V_{TH(MAX)}$, I_{SINK} = 0.5mA, $V_{TH} \geq 1.2V$	--	--	0.3	
RESET Output Voltage High	V_{OH}	1.1V < V_{DD} < $V_{TH(MIN)}$, I_{SOURCE} = 200μA	0.8 V_{DD}	--	--	V
		1.8V < V_{DD} < $V_{TH(MIN)}$, I_{SOURCE} = 500μA	0.8 V_{DD}	--	--	
		3V < V_{DD} < $V_{TH(MIN)}$, I_{SOURCE} = 800μA	V_{DD} –1.5	--	--	


Note 1. Stresses listed as the above “Absolute Maximum Ratings” may cause permanent damage to the device. These are for stress ratings. Functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may remain possibility to affect device reliability.


Note 2. θ_{JA} is measured in the natural convection at T_A = 25°C on a low effective thermal conductivity test board of JEDEC 51-3 thermal measurement standard.


Note 3. Devices are ESD sensitive. Handling precaution is recommended.


Note 4. The device is not guaranteed to function outside its operating conditions.


Typical Operating Characteristics

















Supply Current vs. Input Voltage




Power-Down Reset Delay vs. Temperature




Power-Down Reset Delay vs. Temperature




Power-Down Reset Delay vs. Temperature




Nch Driver Sink Current vs. Input Voltage




Nch Driver Sink Current vs. Input Voltage




Reset Threshold Deviation vs. Temperature




Pch Driver Output Current vs. Input Voltage




Power-Up Reset Time-Out vs. Temperature




Power-Up Reset Time-Out vs. Temperature




Output Delay Time vs. Load Capacitance




Nch Driver Output Current vs. V_{DS}




Nch Driver Output Current vs. Input Voltage




Power Down Reset Time-Out vs. Temperature



Output Voltage vs. Input Voltage



Power-Down Reset Time-Out vs. Temperature




Application Information

Benefits of Highly Accurate Reset Threshold


Most µP supervisor ICs have reset threshold voltages between 1% and 1.5% below the value of nominal supply voltages. This ensures a reset will not occur within 1% of the nominal supply, but will occur when the supply is 1.5% below nominal.

Outline Dimension




Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.800	1.100	0.031	0.044
A1	0.000	0.100	0.000	0.004
B	1.150	1.350	0.045	0.054
b	0.150	0.400	0.006	0.016
C	1.800	2.450	0.071	0.096
D	1.800	2.250	0.071	0.089
e	1.300		0.051	
H	0.080	0.260	0.003	0.010
L	0.210	0.460	0.008	0.018

SC-70-3 Surface Mount Package



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.800	1.100	0.031	0.043
A1	0.000	0.100	0.000	0.004
B	1.150	1.350	0.045	0.053
b	0.150	0.400	0.006	0.016
b1	0.350	0.500	0.014	0.020
C	1.800	2.450	0.071	0.096
D	1.800	2.200	0.071	0.087
e	1.300		0.051	
H	0.080	0.260	0.003	0.010
L	0.200	0.460	0.008	0.018

SC-82 Surface Mount Package



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.889	1.295	0.035	0.051
A1	0.000	0.152	0.000	0.006
B	1.397	1.803	0.055	0.071
b	0.356	0.508	0.014	0.020
C	2.591	2.997	0.102	0.118
D	2.692	3.099	0.106	0.122
e	1.803	2.007	0.071	0.079
H	0.080	0.254	0.003	0.010
L	0.300	0.610	0.012	0.024

SOT-23-3 Surface Mount Package

Richtek Technology Corporation
Headquarter
5F, No. 20, Taiyuen Street, Chupei City
Hsinchu, Taiwan, R.O.C.
Tel: (8863)5526789 Fax: (8863)5526611

Richtek Technology Corporation
Taipei Office (Marketing)
5F, No. 95, Minchiuan Road, Hsintien City
Taipei County, Taiwan, R.O.C.
Tel: (8862)86672399 Fax: (8862)86672377
Email: marketing@richtek.com

Information that is provided by Richtek Technology Corporation is believed to be accurate and reliable. Richtek reserves the right to make any change in circuit design, specification or other related things if necessary without notice at any time. No third party intellectual property infringement of the applications should be guaranteed by users when integrating Richtek products into any application. No legal responsibility for any said applications is assumed by Richtek.