BFG67; BFG67/X; BFG67/XR

NPN 8 GHz wideband transistors

Rev. 05 — 23 November 2007 Product data sheet

IMPORTANT NOTICE

Dear customer,

As from October 1st, 2006 Philips Semiconductors has a new trade name
- NXP Semiconductors, which will be used in future data sheets together with new contact details.
In data sheets where the previous Philips references remain, please use the new links as shown below.

http://www.philips.semiconductors.com use http://www.nxp.com

http://www.semiconductors.philips.com use http://www.nxp.com (Internet)

sales.addresses@www.semiconductors.philips.com use salesaddresses@nxp.com (email)

The copyright notice at the bottom of each page (or elsewhere in the document, depending on the version)
- © Koninklijke Philips Electronics N.V. (year). All rights reserved -
is replaced with:
- © NXP B.V. (year). All rights reserved. -

If you have any questions related to the data sheet, please contact our nearest sales office via e-mail or phone (details via salesaddresses@nxp.com). Thank you for your cooperation and understanding,

NXP Semiconductors

NXP founded by Philips

NPN 8 GHz wideband transistors BFG67; BFG67/X; BFG67/XR

FEATURES

- High power gain
- Low noise figure
- High transition frequency
- Gold metallization ensures excellent reliability.

APPLICATIONS

Wideband applications in the GHz range, such as satellite TV tuners and portable RF communications equipment.

DESCRIPTION


NPN silicon transistor in a 4-pin, dual-emitter SOT143B plastic package. Available with in-line emitter pinning (BFG67) and cross emitter pinning (BFG67/X). Version with reverse pinning (BFG67/XR) also available on request.

MARKING

TYPE NUMBER	CODE
BFG67 (Fig.1)	V3%
BFG67/X (Fig.1)	%MV
BFG67/XR (Fig.2)	V26


PINNING

PIN	DESCRIPTION		
	BFG67	BFG67/X	BFG67/XR
1	collector	collector	collector
2	base	emitter	emitter
3	emitter	base	base
4	emitter	emitter	emitter



Top view MSB014

Fig.1 Simplified outline SOT143B.



Top view MSB035

Fig.2 Simplified outline SOT143R.

QUICK REFERENCE DATA

SYMBOL	PARAMETER	CONDITIONS	TYP.	MAX.	UNIT
V_{CEO}	collector-emitter voltage	open base	–	10	V
I_C	collector current (DC)		–	50	mA
P_{tot}	total power dissipation	$T_s \leq 65$ °C	–	300	mW
C_{re}	feedback capacitance	$I_C = i_c = 0$; $V_{CB} = 8$ V; f = 1 MHz	0.5	–	pF
f_T	transition frequency	$I_C = 15$ mA; $V_{CE} = 8$ V; f = 500 MHz	8	–	GHz
G_{UM}	maximum unilateral power gain	$I_C = 15$ mA; $V_{CE} = 8$ V; $T_{amb} = 25$ °C; f = 1 GHz	17	–	dB
F	noise figure	$\Gamma_s = \Gamma_{opt}$; $I_C = 5$ mA; $V_{CE} = 8$ V; $T_{amb} = 25$ °C; f = 1 GHz	1.3	–	dB
		$\Gamma_s = \Gamma_{opt}$; $I_C = 5$ mA; $V_{CE} = 8$ V; $T_{amb} = 25$ °C; f = 2 GHz	2.2	–	dB

LIMITING VALUES

In accordance with the Absolute Maximum Rating System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
V_{CBO}	collector-base voltage	open emitter	–	20	V
V_{CEO}	collector-emitter voltage	open base	–	10	V
V_{EBO}	emitter-base voltage	open collector	–	2.5	V
I_C	collector current (DC)		–	50	mA
P_{tot}	total power dissipation	$T_s \leq 65$ °C; see Fig.3; note 1	–	380	mW
T_{stg}	storage temperature range		–65	150	°C
T_j	junction temperature		–	175	°C

Note

1. T_s is the temperature at the soldering point of the collector pin.

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	CONDITIONS	VALUE	UNIT
$R_{th\ j\text{-}s}$	thermal resistance from junction to soldering point	note 1	290	K/W

Note

1. T_s is the temperature at the soldering point of the collector pin.




Fig.3 Power derating curve.


CHARACTERISTICS

T_j = 25 °C unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
I_{CBO}	collector leakage current	V_{CB} = 5 V; I_E = 0	–	–	50	nA
h_{FE}	DC current gain	I_C = 15 mA; V_{CE} = 5 V	60	100	–	
f_T	transition frequency	I_C = 15 mA; V_{CE} = 8 V; f = 500 MHz	–	8	–	GHz
C_c	collector capacitance	$I_E = i_e$ = 0; V_{CB} = 8 V; f = 1 MHz	–	0.7	–	pF
C_e	emitter capacitance	$I_C = i_c$ = 0; V_{EB} = 0.5 V; f = 1 MHz	–	1.3	–	pF
C_{re}	feedback capacitance	$I_C = i_c$ = 0; V_{CB} = 8 V; f = 1 MHz	–	0.5	–	pF
G_{UM}	maximum unilateral power gain; note 1	I_C = 15 mA; V_{CE} = 8 V; T_{amb} = 25 °C; f = 1 GHz	–	17	–	dB
		I_C = 15 mA; V_{CE} = 8 V; T_{amb} = 25 °C; f = 2 GHz	–	10	–	dB
F	noise figure	$\Gamma_s = \Gamma_{opt}$; I_C = 5 mA; V_{CE} = 8 V T_{amb} = 25 °C; f = 1 GHz	–	1.3	–	dB
		$\Gamma_s = \Gamma_{opt}$; I_C = 15 mA; V_{CE} = 8 V; T_{amb} = 25 °C; f = 1 GHz	–	1.7	–	dB
		I_C = 5 mA; V_{CE} = 8 V; T_{amb} = 25 °C; f = 2 GHz; Z_S = 60 Ω	–	2.5	–	dB
		I_C = 15 mA; V_{CE} = 8 V; T_{amb} = 25 °C; f = 2 GHz; Z_S = 60 Ω	–	3	–	dB


Note

1. G_{UM} is the maximum unilateral power gain, assuming S_{12} is zero and $G_{UM} = 10 \log \frac{|S_{21}|^2}{(1-|S_{11}|^2)(1-|S_{22}|^2)}$ dB.




V_{CE} = 5 V.

Fig.4 DC current gain as a function of collector current.




$I_C = i_c = 0$; f = 1 MHz.

Fig.5 Feedback capacitance as a function of collector-base voltage.



V_{CE} = 8 V; T_{amb} = 25 °; f = 2 GHz.


Fig.6 Transition frequency as a function of collector current.



V_{CE} = 8 V; f = 1 GHz.

G_{UM} = maximum unilateral power gain;
MSG = maximum stable gain;
G_{max} = maximum available gain.


Fig.7 Gain as a function of collector current.



V_{CE} = 8 V; I_C = 5 mA.

G_{UM} = maximum unilateral power gain;
MSG = maximum stable gain;
G_{max} = maximum available gain.


Fig.8 Gain as a function of frequency.



V_{CE} = 8 V; I_C = 15 mA.

G_{UM} = maximum unilateral power gain;
MSG = maximum stable gain;
G_{max} = maximum available gain.


Fig.9 Gain as a function of frequency.



V_{CE} = 8 V; I_C = 30 mA.


G_{UM} = maximum unilateral power gain;
MSG = maximum stable gain;
G_{max} = maximum available gain.

Fig.10 Gain as a function of frequency.



V_{CE} = 8 V.

Fig.11 Minimum noise figure as a function of collector current.



V_{CE} = 8 V.


Fig.12 Minimum noise figure as a function of frequency.

BFG67/X

f (MHz)	V_{CE} (V)	I_C (mA)
500	8	5

Noise Parameters

F_{min} (dB)	Gamma (opt)		$R_n/50$
	(mag)	(ang)	
0.95	0.455	33.8	0.288



Z_O = 50 Ω.


Fig.13 Noise circle figure.

BFG67/X

f (MHz)	V_{CE} (V)	I_C (mA)
1000	8	5

Noise Parameters

F_{min} (dB)	Gamma (opt)		$R_n/50$
	(mag)	(ang)	
1.3	0.375	65.9	0.304



Z_O = 50 Ω.

Fig.14 Noise circle figure.

BFG67/X


f (MHz)	V_{CE} (V)	I_C (mA)
2000	8	5

Noise Parameters

F_{min} (dB)	Gamma (opt)		$R_n/50$
	(mag)	(ang)	
2.2	0.391	136.5	0.184


Average Gain Parameters

G_{MAX} (dB)	Gamma (max)	
	(mag)	(ang)
12	0.839	–170




Z_O = 50 Ω.

Fig.15 Noise circle figure.




V_{CE} = 8 V; I_C = 15 mA; Z_O = 50 Ω.

Fig.16 Common emitter input reflection coefficient (S_{11}).




V_{CE} = 8 V; I_C = mA; Z_O = 50 Ω.

Fig.17 Common emitter forward transmission coefficient (S_{21}).



V_{CE} = 8 V; I_C = 15 mA.

Fig.18 Common emitter reverse transmission coefficient (S_{12}).




V_{CE} = 8 V; I_C = 15 mA.

Fig.19 Common emitter output reflection coefficient (S_{22}).

PACKAGE OUTLINES

Plastic surface mounted package; 4 leads **SOT143B**




DIMENSIONS (mm are the original dimensions)

UNIT	A	A_1 max	b_p	b_1	c	D	E	e	e_1	H_E	L_p	Q	v	w	y
mm	1.1 0.9	0.1	0.48 0.38	0.88 0.78	0.15 0.09	3.0 2.8	1.4 1.2	1.9	1.7	2.5 2.1	0.45 0.15	0.55 0.45	0.2	0.1	0.1

OUTLINE VERSION	REFERENCES				EUROPEAN PROJECTION	ISSUE DATE
	IEC	JEDEC	EIAJ			
SOT143B						97-02-28

Plastic surface mounted package; reverse pinning; 4 leads **SOT143R**



DIMENSIONS (mm are the original dimensions)

UNIT	A	A_1 max	b_p	b_1	c	D	E	e	e_1	H_E	L_p	Q	v	w	y
mm	1.1 0.9	0.1	0.48 0.38	0.88 0.78	0.15 0.09	3.0 2.8	1.4 1.2	1.9	1.7	2.5 2.1	0.55 0.25	0.45 0.25	0.2	0.1	0.1

OUTLINE VERSION	REFERENCES				EUROPEAN PROJECTION	ISSUE DATE
	IEC	JEDEC	EIAJ			
SOT143R						97-03-10

Legal information

Data sheet status

Document status[1][2]	Product status[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nxp.com.

Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Disclaimers

General — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) may cause permanent damage to the device. Limiting values are stress ratings only and operation of the device at these or any other conditions above those given in the Characteristics sections of this document is not implied. Exposure to limiting values for extended periods may affect device reliability.

Terms and conditions of sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nxp.com/profile/terms, including those pertaining to warranty, intellectual property rights infringement and limitation of liability, unless explicitly otherwise agreed to in writing by NXP Semiconductors. In case of any inconsistency or conflict between information in this document and such terms and conditions, the latter will prevail.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

Contact information

For additional information, please visit: **http://www.nxp.com**

For sales office addresses, send an email to: **salesaddresses@nxp.com**