Digital transistors (built-in resistors)

DTC363EU / DTC363EK / DTC363ES

●Features


In addition to the features of regular digital transistors,

1) Low $V_{O(on)}$ makes these transistors optimal for muting circuits.
   $V_{O(on)}$=40mV (typ.)
   (I_O / I_I=50mA / 2.5mA)
2) They can be used at high current (I_C=600mA).

●Structure


NPN digital transistor
(Built-in resistor type)

●Equivalent circuit



●External dimensions (Unit : mm)

DTC363EU




ROHM : UMT3
EIAJ : SC-70

Addreviated symbol : H27

(1) GND
(2) IN
(3) OUT

DTC363EK




ROHM : SMT3
EIAJ : SC-59

Addreviated symbol : H27

(1) GND
(2) IN
(3) OUT

DTC363ES



ROHM : SPT
EIAJ : SC-72

(1) GND
(2) OUT
(3) IN

●**Absolute maximum ratings** (Ta=25°C)

Parameter	Symbol	Limits(DTC363E□)			Unit
		U	K	S	
Supply voltage	V_{CC}	20			V
Input voltage	V_{IN}	−10 to +10			V
Output current	I_C	600			mA
Power dissipation	Pd	200		300	mW
Junction temperature	Tj	150			℃
Storage temperature	Tstg	−55 to +150			℃

●**Electrical characteristics** (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	$V_{I(off)}$	–	–	0.5	V	V_{CC}=5V, I_O=100μA
	$V_{I(on)}$	2	–	–		V_O=0.3V, I_O=10mA
Output voltage	$V_{O(on)}$	–	40	80	mV	I_O/I_I=50mA/2.5mA
Input current	I_I	–	–	1.3	mA	V_I=5V
Output current	$I_{O(off)}$	–	–	0.5	μA	V_{CC}=15V, V_I=0V
DC current gain	G_I	70	–	–	–	V_O=5V, I_O=50mA
Input resistance	R_1	4.76	6.8	8.84	kΩ	–
Resistance ratio	R_2/R_1	0.8	1	1.2	–	–
Transition frequency	f_T	–	200	–	MHz	V_{CE}=10V, I_E= −50mA, f=100MHz ＊
Output "ON" resistance	R_{on}	–	1.0	–	Ω	V_I=7V, R_L=1kΩ, f=1kHz

＊Transition frequency of the device

●**Packaging specifications**

Part No.	Package	UMT3	SMT3	SPT
	Packaging type	Taping	Taping	Taping
	Code	T106	T146	TP
	Basic ordering unit (pieces)	3000	3000	5000
DTC363EU		○	–	–
DTC363EK		–	○	–
DTC363ES		–	–	○




Fig.1 Input "ON" resistance (R_{on}) measurement circuit

●**R_{on} measurement circuit**

●Electrical characteristic curves




Fig.2 Input voltage vs. output current (ON characteristics)




Fig.3 Output current vs. input voltage (OFF characteristics)




Fig.4 DC current gain vs. output current




Fig.5 Output voltage vs. output current




Fig.6 "ON" resistance vs. input voltage

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).
Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.
In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.