High transition frequency (dual transistors)


UMX21N

●Features

1) Two 2SC4713K chips in a UMT package.
2) Very low output-on resistance. (Ron)
3) Low capacitance.

●Dimensions (Unit : mm)

UMX21N




ROHM : UMT6
EIAJ : SC-88

Each lead has same dimensions

●Equivalent circuits

UMX21N



●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit	
Collector-base voltage	V_{CBO}	12	V	
Collector-emitter voltage	V_{CEO}	6	V	
Emitter-base voltage	V_{EBO}	3	V	
Collector current	I_C	50	mA	
Collector power dissipation	P_C	150	mW	*
Junction temperature	Tj	150	°C	
Storage temperature	Tstg	−55 to +150	°C	

* 120mW per element must not be exceeded.

●Package, marking, and packaging specifications

Type	UMX21N
Package	UMT6
Marking	X21
Code	TR
Basic ordering unit (pieces)	3000

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	12	–	–	V	I_C=10μA
Collector-emitter breakdown voltage	BV_{CEO}	6	–	–	V	I_C=1mA
Emitter-base breakdown voltage	BV_{EBO}	3	–	–	V	I_E=10μA
Collector cutoff current	I_{CBO}	–	–	0.5	μA	V_{CB}=10V
Emitter cutoff current	I_{EBO}	–	–	0.5	μA	V_{EB}=2V
Collector-emitter saturation voltage	$V_{CE(sat)}$	–	–	0.3	V	I_C/I_B=10mA/1mA
DC current transfer ratio	h_{FE}	270	–	560	–	V_{CE}/I_C=5V/10mA
Transition frequency	f_T	300	800	–	MHz	V_{CE}=5V, I_E= −10mA, f=200MHz
Output capacitance	Cob	–	1	1.7	pF	V_{CB}=10V, I_E=0A, f=1MHz
Output-on resistance	Ron	–	2	–	Ω	I_B=3mA, V_I=100mVrms, f=500kHz

This product might cause chip aging and breakdown under the large electrified environment.
Please consider to design ESD protection circuit.

●**Electrical characteristics curves**




Fig.1 Grounded emitter output characteristics (I)




Fig.2 Grounded emitter output characteristics (II)




Fig.3 Grounded emitter propagation characteristics




Fig.4 DC current gain vs. collector current




Fig.5 Collector-emitter saturation voltage vs. collector current




Fig.6 Gain bandwidth product vs. collector current




Fig.7 Collector output capacitance vs. voltage




Fig.8 Back capacitance voltage




Fig.9 Output-on resistance vs. base current

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).
Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.
It is our top priority to supply products with the utmost quality and reliability. However, there is always a chance of failure due to unexpected factors. Therefore, please take into account the derating characteristics and allow for sufficient safety features, such as extra margin, anti-flammability, and fail-safe measures when designing in order to prevent possible accidents that may result in bodily harm or fire caused by component failure. ROHM cannot be held responsible for any damages arising from the use of the products under conditions out of the range of the specifications or due to non-compliance with the NOTES specified in this catalog.

Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact your nearest sales office.

ROHM Customer Support System

THE AMERICAS / EUPOPE / ASIA / JAPAN

www.rohm.com

Contact us : webmaster@rohm.co.jp

Copyright © 2007 ROHM CO.,LTD.

ROHM CO., LTD. 21, Saiin Mizosaki-cho, Ukyo-ku, Kyoto 615-8585, Japan
TEL : +81-75-311-2121
FAX : +81-75-315-0172